



Datenblatt - Fiche technique - Data sheet

**12.02.1008**



ROLINE RS232 nach RS422/485 Konverter für DIN Hutschiene, selfpowered

ROLINE Convertisseur RS232 vers RS422/485 pour rail DIN auto-alimenté

ROLINE RS-232 to RS-422/485 Converter, Din Rail, self powered

Item no.: 12.02.1008

## ROLINE RS232-RS422/485 Converter, Self powered



### Features:

- High Speed Baud Rate up to 921.6Kbps
- Built-in Terminator 120 ohm for DIP Switch Setting
- Max 10-device connectivity for 4 Wire RS-485(RS-422 Multi-Drop) Mode
- Max 32-device connectivity for RS-485 Mode
- Communication status can be monitored through LED
- 600W Surge Protection
- Built-in 15KV ESD protection for all Serial Port and RS-422/485 Signals Protection
- Supports Industrial Specification
- No Driver Needs
- RS-422/485 Connector: Terminal Block 7 Pin 5.08mm
- RS-232 Connector: DB9 Female
- Non power input
- DC jack for external power adapter(optional)  
Suggested power input 10~30VDC @24VDC 39.5mA MAX
- Max 1.2Km by 115.2Kbps.